

ANTIHELD

DC Jack

Connection for power supply.

User Manual

Please read the enclosed safety instructions before first use!

INPUT

Effect input. Connect the instrument or another effect device.

OUTPUT

Effect output. Connect the amplifier or another effect device.

GAIN

Sets the degree of amplification/distortion of the signal. Turning clockwise increases intensity.

LEVEL

Sets the volume of the effect. To increase output level, turn the knob clockwise.

BYPASS Switch

Turns the effect on and off. An active effect is indicated by the LED.

TONE

Balance between bass and treble, shape your sound with precision.

MODERN / CLASSIC

Switch tonal character between 'Modern' and 'Classic'.

True Bypass

The relay-based intelligent true bypass has a 'momentary' function. The pedal is only activated/deactivated while the footswitch is held down. With a short press, the bypass works as a classic switch. It is also possible to program whether the pedal is active or inactive on power-up. To set this, hold down the bypass switch while plugging in the DC connector. The power LED will blink to indicate the state has been changed.

MIX

Control for blending the clean signal with the distorted signal.

MIDS

Shape your sound with high precision, from growling tones to cutting sounds.

Assembly and Setup:

1. Unpack the device.
2. Place the device on a non-slip surface (e.g. rubber mat) or mount it securely on a pedalboard.
3. Ensure the pedal is securely mounted and cannot slip.
4. Plug the DC power connector with the specified voltage/current into the DC jack (see diagram).
5. The power LED (the bird) should light up after pressing the bypass switch.

6. Connect the audio devices:

- a. Audio Input: Connect a guitar/bass or another pedal.
- b. Audio Output: Connect to the input of another pedal or your amplifier.

7. The pedal may become slightly warm during operation. Ensure proper ventilation.

General Notes:

- Depending on input signal, knob settings, amplifier, and speakers, extreme volume levels may occur. Use hearing protection.
- Operate knobs and switches properly and gently. Do not force controls.
- The intended use of this product follows the quick setup guide. Contact support if you have

questions.

Technical Data:

Input impedance: HIGH

Output impedance: LOW

Recommended load: >10k Ohm

Dimensions: 55mm x 120mm x
60mm (HxLxW)

Weight: 340g

Power supply: 9V DC, 2.1mm
barrel plug (center negative) -
60mA

Input: 6.3mm jack

Output: 6.3mm jack

Operating temperature: 0-35°C

Storage temperature: -20 to 50°C

Protection class: III